

“EPF” MOTOR CONTROL PANEL

DUPLEX

230V, 1 PHASE

FEATURES:

ENCLOSURE

- ◆ NEMA 4x Fiberglass (18”x16”x10”)
- ◆ Stainless Steel Hinges
- ◆ Quick Release Stainless Steel Draw Latches
- ◆ WATERTIGHT

ALARM LIGHT

- ◆ Shatter Resistant Red Lens
- ◆ NEMA 4x Rating
- ◆ Standard 40 Watt Appliance Bulb
- ◆ Easy Bulb Replacement Design

CONTROL CIRCUIT FUSES

- ◆ 3A Control Circuit Fuse
- ◆ 3A Alarm Circuit Fuse
- ◆ Type Bussman

PUMP CIRCUIT BREAKERS

- ◆ Thermal & Magnetic Trip
- ◆ Type Square D

MOTOR STARTERS

- ◆ IEC Rated
- ◆ FLC Adjustment Dial
- ◆ Visual Trip Indicator
- ◆ Lockable Settings Cover
- ◆ Class 10 Tripping Overload
- ◆ Single Phase Sensitivity

MODEL 100SF CONTROLLER

- ◆ Hand-Off-Auto Switches For Each Pump
- ◆ Pump Run Indicator Lights For Each Pump
- ◆ Seal Failure Indicator Lights For Each Pump
- ◆ Seal Failure Test Switch
- ◆ Alternation
- ◆ Lead Pump Selector Switch
- ◆ Alarm Test Switch
- ◆ Plug In Design For Ease Of Maintenance

MOTOR STARTING CIRCUIT

- ◆ Start Capacitors
- ◆ Run Capacitors
- ◆ Start Relays with wire Identifications

